

AX-1250

8 Zone, 13 Source Multi-Room Controller with Amplifier

8 Zones, 13 Sources + 32 distributed sources

The AX-1250 features 6 powered zones delivering 55 watts per speaker and 2 independent preamp zones.

12 physical sources - 8 combined digital/analog and 4 dedicated digital coax/optical inputs plus a Network Audio decoder that can stream from the local network, the Internet or a mobile device (phone or tablet) connected to the network.

Add to that the ability to access up to 32 distributed sources from any compatible amplifier on the network (AX-1250 and Mini 4) and you will not be running out of inputs any time soon!

Unrivalled Connectivity

USB (for configuration only), IR BUS (legacy keypad) and Ethernet connectivity, 10 buffered IR outputs, 2 lit doorbell compatible input triggers, individual amp ons, keypad connections and dual network ports offering unrivalled connectivity of up to 96 Zones.

Endless Control

The internal webpage has unique customisation allowing IR commands to be attached to buttons for source control. User based source and zone lockout via customisable user accounts and the ability for built-in automation via Zone and Source event triggers.

Audio Control

600ms of audio delay for each zone per source (totaling 64 delay settings), 18dB of analog source gain adjustment, Bass, Treble, balance and loudness per zone and a sub-woofer preamp filter.

iOS and Android App

By using the FREE app you can use the Amplifier as a controller with macro capability. Add the KPC-N 2.8" colour touchscreen and enjoy full two way communications from each zone on both interfaces.



SPECIFICATIONS

- 55 Watts per channel @8Ω (4Ω capable for 3 zones)
- Local mobile device music playback (iOS and Android) and UPnP push functionality
- Fully implemented UPNP server
- Auto zone On/Off via source audio sensing
- Expandable to 96 zones (via network expansion)
- Bass, Treble, Balance and Loudness per zone
- 12 Audio Sources:
 - S1 - 8 either Analogue, or Digital Coax (PCM)
 - S9 - 12 either Digital Coax or Optical (PCM)
- S13 – Ethernet/Internet stream. HD audio and Compression free formats supported
- Up to 10 seconds of 44.1 KHz 16 Bit stereo audio for the doorbells
- 10 Buffered IR outputs
 - 1 - 8 routing
 - 9 - 10 summed
- Internal Web Page with user access control and setup
- iOS and Android compatible via FREE app
- Keypad/IR connection for every zone
- Control4 driver available – FREE (net and UPnP function not supported)

Part Number 93119

Accessories AX-KPC2.8 LCD Touch Panel Part# 93112
 AX-KPD Keypad with 1.5" LCD display Part# 93111
 AX-R4 Controller/Router Part# 93113

Manual URL www.currentaudio.com

