

AX-400DA

4 Zone, 6 Source Multi Room Controller with Amplifier

Like its bigger brother the AX-800DA has been re-engineered from the ground up, including many of the features found in the AX-8000DAV.

The 4 powered zones deliver the same 50 watts per speaker that all Axium owners have come to appreciate, & with the added functionality of being able to be stacked with the AX-800DAV expansion is now even more flexible.

Of course there is USB, RS232 & Ethernet connectivity, routed IR outputs, 2 lit doorbell compatible triggers, amp on's, individual keypad connections, a legacy keypad connector & an amplifier expansion port offering unrivalled connectivity up to 96 zones.

The internal webpage has unique customisation allowing IR commands to be attached to buttons for source control from within the webpage. Add an AX-400DA to a legacy 452/4750 Axium system and enjoy webpage control of all the zones.

With adjustable input levels, more presets, wider zone linking, 2 doorbell inputs for stored music with more memory for longer playback, massively improved standby & operational efficiencies and a significant refinement in sound quality, like the AX-800DAV this is an evolutionary leap forward.

There are no more excuses... Prepare to be spellbound in every room.



SPECIFICATIONS

Rated Output Power (FTC)	50 Watts / channel, 8Ω loads
All Channels:	
Speaker Impedance (Z1 – Z6 L/R)	4Ω - 8Ω
Input Sensitivity and Impedance (S1 – S6 L/R)	0.72 V / 22KΩ (Unbalanced)
Frequency Response	20Hz – 20 KHz / – 3dB (8Ω)
THD (Total Harmonic Distortion)	0.1% (40 Watt, 8 load)
Signal to Noise Ratio	100dB (IHA-A, 1V input / unbalanced)
Frequency Response	20 Hz to 20 kHz
Total Harmonic Distortion (Unbridged or Bridged)	0.1% THD 20 Hz to 20 kHz
IR Output	Eight 3.5mm Jack: IR1 – IR6 and SUM IR1-IR6: Current limited to 25mA
Expansion Bus	One Dual RJ45 Socket: Axium Bus, Summed IR
Ethernet	One Shielded RJ45 socket – 100Base T
RS232	One Isolated DB9 – 9600 Baud
USB	One USB mini-B 5 pin
Controller	Four RJ45 socket: PORT1 – PORT4 One 4 way terminal plug (0V, IR, 12V & Data)
Amp On & PG Control	One 8 way terminal plug with Amp ON 1 – 4 and Two Page preset contact closure inputs: PG1 & PG2.
Power Consumption	320 W
Standby Power Consumption	4W
Dimensions WxHxD (weight)	17 1/8" (435mm) x 4 1/8" (105mm) x 15 3/8" (390mm) (15 lbs.)

Part Number 93109

Accessories AX-KPC2.8 LCD Touch Panel Part# 93112
AX-KPD Keypad with 1.5" LCD display Part# 93111
AX-R4 Controller/Router Part# 93113

Manual URL www.currentaudio.com

