

PICO-PRO

Signal Analysis Meter with Reverse Path



Features

- 5~870 MHz Operation including SUB-VHF forward and reverse signal measurement
- 4 Channel plans enables easy switching between Off-Air and CATV signals
- Frequency or channel selection provides compatibility with channel or data, and other narrow bandwidth carriers
- Full spectrum scan provides display of up to 100 channels simultaneously
- Tilt measurement feature provides for simplified system balancing
- Carrier-to-noise and hum testing provides system performance testing
- Large easy-to-read graphic LCD display provides quick-glance signal reference
- AC/DC voltage compatibility allows RF and AC/DC measurements without changing test equipment
- Automatic power shut-off feature extends time between recharges
- Bright orange high impact plastic housing and soft leatherette-nylon protective case with belt clip included

Specification

Frequency

Frequency Range	5~870 MHz
Resolution Ratio	10 kHz
Measured Bandwidth	280 kHz

Level Measurement

Measurement Range	-35~60 dBmV
Measurement Accuracy	±1.5 dB
Resolution Ratio	0.1 dB
Method of Detection	Peak detection
Input Resistance	75 Ω

Voltage Measurement

Input Range	0~80 V AC/DC
Measurement Accuracy	±2 V
Resolution Ratio	0.1 V

Ordering Information

PICO-PRO	Signal Analysis Meter with Reverse Path
PICO-PRO-BT	Replacement Battery
PICO-PRO-PS	Power Supply