

**Datavideo SE-500HD 4-Channel HDMI 1080p video switcher with built-in audio mixer**

<b>Model Name</b>	SE-500HD
<b>Product Name</b>	HD/SD 4-Channel Digital Video Switcher
<b>Video Standard</b>	HD & SD
<b>Video Format</b>	1080p 50/59.94/60Hz 1080i 50/59.94/60Hz 720p 50/59.94/60Hz 576i 50Hz 480i 59.94Hz
<b>Video Processing</b>	HDMI: YUV 4:4:4 10 bit, RGB: 4:4:4
<b>Input Routable / Crosspoint</b>	N/A
<b>Video Input</b>	4x HDMI
<b>Mix HD &amp; SD source</b>	Yes
<b>Computer Graphic Interface</b>	4 via HDMI
<b>Video output</b>	2x HDMI (1 is MV, 1 is PGM)
<b>Down-converted output</b>	Yes
<b>Built-in Multi-view monitoring out</b>	HDMI
<b>Audio input</b>	1x Stereo RCA (UR) 2x Mono Microphone De-embedded Digital Audio (2 CH)
<b>Audio output</b>	1x Stereo RCA (UR) 1x Stereo headphone (Mini Jack with volume control) Embedded Digital Audio (2 CH)
<b>Embedded audio support</b>	embedded 2-CH digital/analogue audio
<b>Audio Delay Calibration</b>	N/A
<b>A+V switching</b>	Yes
<b>Chromakey</b>	N/A
<b>Title Creator</b>	N/A
<b>USK</b>	Lumakey
<b>DSK</b>	N/A
<b>Picture in Picture</b>	1
<b>Logo Insertion</b>	N/A
<b>Still Store</b>	N/A
<b>Effects</b>	FTB, Cut, Wipe with border
<b>Transition Preview</b>	N/A
<b>Sync / Reference In/Out</b>	Built-in Genlock (internal)
<b>Tally Output</b>	1x D-sub 15pin, dual color
<b>PC Remote Control</b>	N/A
<b>Built-in Audio Mixer</b>	4 channels
<b>Chassis</b>	Unibody
<b>Power</b>	DC 12V