

Roland XI-DANTE Dante Expansion Interface

| | |
|-----------------------|---|
| Channels | Up to 64 channels input Up to 64 channels output * The number of available channels will be changed by Sampling Frequency or the attached device. |
| Signal Processing | Sampling Frequency 96 kHz, 48 kHz, 44.1 kHz |
| Data Length | 24 bits |
| Connectors | PRIMARY port: RJ-45 XLR type SECONDARY port: RJ-45 XLR type CONTROL port: RJ-45 type USB COMPUTER port: USB type B (inside of the panel, updates only) |
| Indicators | LINK/ACT x 3 1G x 1 |
| Power Consumption | 5.0 W |
| Dimensions | 120 (W) x 185 (D) x 40 (H) mm 4-3/4 (W) x 7-5/16 (D) x 1-5/8 (H) inches * Protruding parts not included. |
| Weight | 192 g 7 oz |
| Operation Temperature | +5 to +40 degrees Celsius +41 to +104 degrees Fahrenheit |
| Accessories | Setup Guide Connector cap x 2 Connector cover x 2 Ferrite core x 2 |