

BZBGEAR BG-CJ-RS Serial PTZ Joystick Controller (RS-232/422/485)

| | |
|---------------------------|--|
| Protocol | Pelco-D, Pelco-P, VISCA |
| Baud rate(bps) | 1200bps, 2400bps, 4800bps, 9600bps, 19200bps |
| Control Address | Control 255pcs PTZ at the most, address code: 0-254 |
| Communication Mode | RS485 half-duplex, RS422 full-duplex, RS232 serial port 10M internet (select to order), USB (select to order) |
| Communication Range | RS485, RS422: 1200m, RS232: 10m |
| Cascade connection number | 16 sub-control at most, controller ID:0-15 |
| Joystick | 3D (control: up, down, left, right, zoom) |
| Interface Mode | 10PIN pressing line port, DB9 connector |
| Display | Blue LCD |
| Warning Tone | Key-touch beep on/off |
| Power Supply | DC12V±10% |
| Power Consumption | 6W MAX |
| Working Temperature | 32°F - 122°F / 0°C - 50°C |
| Store Temperature | -4°F - 158°F / -20°C - 70°C |
| Dimension (L x W x H) | 13 x 7.1 x 4.3in [320 x 179.3 x 109.9mm] |
| Weight | 6.17 lbs [2.8 Kg] |