

**Current Audio AMP1270 6 Zone/12 Channel Amplifier with Auto-Sensing and Dual Global Inputs**

Continuous Power	70 Watts RMS at 4 ohms
OutputAll channels driven	50 Watts at 8 ohms
Bridged Power Output	140 Watts per channel RMS at 8 ohms
All channels driven	Caution: Maintain an 8 ohm load in the bridged mode
Standby Power	< 1 watt
Power Consumption	1100 watts
Input Sensitivity/Impedance	500mv /20,000 ohms
Signal to Noise Ratio	95 db
Frequency Response	20 Hz to 20 kHz
Total Harmonic Distortion (Unabridged or Bridged)	0.1% THD 20 Hz to 20 kHz
Dimensions WxHxD (weight)	17" (431.8mm) x 4" (101.6mm) x 13" (330.2mm) (32 lbs.)