

Current Audio AX-400DA 4 Zone/6 Source Multi Room Controller with Amplifier

Rated Output Power (FTC) All Channels:	50 Watts / channel, 80 loads
Speaker Impedance (Z1 - Z6 L/R)	4Ω - 8Ω
Input Sensitivity and Impedance (SI - S6 L/R)	0.72 V/22KΩ (Unbalanced)
Frequency Response	20Hz - 20 KHz / - 3dB (80)
THD (Total Harmonic Distortion)	0.1% (40 Watt, 8 load)
Signal to Noise Ratio	100dB (IHA-A, 1V input / unbalanced)
Frequency Response	20 Hz to 20 kHz
Total Harmonic Distortion (Unabridged or Bridged)	0.1% THD 20 Hz to 20 kHz
IR Output	Eight 3.5mm Jack: IR1 - IR6 and SUM IR1-IR6: Current limited to 25mA
Expansion Bus	One Dual RJ45 Socket: Axium Bus, Summed IR
Ethernet	One Shielded RJ45 socket - 1 OOBBase T
RS232	One Isolated DB9 - 9600 Baud
USB	One USB mini-B 5 pin
Controller	Four RJ45 socket: PORT1 - PORT4 One 4 way terminal plug (0V, IR, 12V & Data)
Amp On & PG Control	One 8 way terminal plug with Amp ON 1 - 4 and Two Page preset contact closure inputs: PG1 & PG2.
Power Consumption	320 W
Standby Power Consumption	4W
Dimensions WxHxD (weight)	17 1/8" (435mm) x 4 1/8" (105mm) x 15 3/8" (390mm) (15 lbs.)