

Ashly LX-308B Mixer 8 Input Stereo Line/1U

Specifications	Note: OdBu = 0.775 VRMS
Distortion, Hum and Noise 20Hz-20kHz	
THD @ +20 dBu, 20Hz—20kHz	<0.02%
IMD (SMPTE) § +20dBu	<0.01%
Residual Output Noise (all levels @ min)	<-100dBu
Master Out, Level & 1 Input Level @ nominal	<-90dBu
Voltage Gain (dBtI)	
Inputs or Sub-inputs to Master Outputs (levels § nominal)	0dB
Input to Master Output (levels @ max)	30dB
Input in Mic Position to Master Outputs (chi or ch2)	61dB
Sub-inputs to Master Outputs (master level @ max)	15dB
Crosstalk	
Adjacent Inputs or Input to Output (@ 1kHz)	<-80dB
Adjacent Inputs or Input to Output (@ 20kHz)	<-60dB
Metering	
VU Meters	Two 5-segment LED meters, OVU = +4dBu
Peak Indicators	Activated when internal signal is 3dB below clipping
Weights, Dimensions & Power	
Unit Weight	7.7lbs (3.5kg)
Shipping Weight	10lbs(5kg)
Dimensions	19"Wx1.75"Hx9.4D" (483mm x 44mm x 239mm)
Power Requirements	100-240VAC, 50-60Hz, 30W