

Kramer 914 Stereo Power Amplifier/100 Watts per Channel

INPUT

- 1 balanced stereo +4dBu/10kΩ on a 5-pin removable terminal block

OUTPUT

- 1 stereo or bridged mono speaker output on a 4-pin removable large terminal block

INPUT SENSITIVITY

- 0.3V to 1.23V — 10dBu to 4 dBu

OUTPUT POWER

- 2x100W @4Ω, 2x50W @8Ω, 1x200W @8Ω BTL

AMPLIFIER TYPE

- Class D

MAXIMUM VOLTAGE GAIN

- 22.7dB

BANDWIDTH (-3DB)

- 20Hz to 20kHz

S/N RATIO

- -70dB @ 14dBu amplification

CONTROLS

- Screw trimmer for line input sensitivity, remote 10k trimmer, contact-closure controls for mute and standby

AUDIO THD+NOISE

- 0.05% @75W RMS @4Ω 6.67kHz

AUDIO 2ND HARMONIC

- 0.08% @75W RMS @4Ω 6.67kHz

POWER SOURCE

- See label near rear panel power socket:
- USA version: 100-120V AC, 50/60Hz, 360VA; European version: 200-240V AC, 50/60Hz, 420VA

INCLUDED ACCESSORIES

- Power cord, mounting bracket

OPTIONS

- RK-1 19" rack adapter

PRODUCT DIMENSION

- 21.46cm x 16.30cm x 4.36cm (8.45" x 6.42" x 1.72") W, D, H

PRODUCT WEIGHT

- 1.3kg (2.8lbs) approx

SHIPPING DIMENSION

- 40.50cm x 29.70cm x 9.00cm (15.94" x 11.69" x 3.54") W, D, H

SHIPPING WEIGHT

- 1.7kg (3.8lbs) approx