

Kramer FC-404Net 4X4 Dante Interface

INPUTS:	4 balanced stereo audio on terminal blocks.
OUTPUTS:	4 balanced stereo audio on terminal blocks.
PORTS:	1 Dante network on RJ-45 connector, 1 RS-232 on a three-pin terminal block, 1 USB mini connector (not used).
INDICATOR LEDS:	On, In/Out Clipping, Sys, Sync.
CONTROLS:	Line/mic+phantom DIP-switches, factory reset button.
BALANCED INPUT LEVEL MAX:	3.2Vpp @ 0dB in/out gain and 0dB output volume.
FREQUENCY RESPONSE:	20Hz to 20kHz @1dB.
THD+N:	<0.008% @1kHz at maximum level.
S/N RATIO:	>85dB.
CROSSTALK:	<80dB.
INPUT GAIN ADJUSTMENT:	-12dB to +60dB.
OUTPUT GAIN ADJUSTMENT:	+9 dB to -80dB.
INPUT IMPEDANCE:	10k Ω balanced.
OUTPUT IMPEDANCE:	50 Ω balanced.
MIC PHANTOM POWER:	+48V DC \pm 10% OPERATING TEMPERATURE:0 $^{\circ}$ to +40 $^{\circ}$ C (32 $^{\circ}$ to 104 $^{\circ}$ F).
STORAGE TEMPERATURE:	-40 $^{\circ}$ to +70 $^{\circ}$ C (-40 $^{\circ}$ to 158 $^{\circ}$ F).
HUMIDITY:	10% to 90%, RHL non-condensing.
POWER CONSUMPTION:	5V DC, 850mA max.
DIMENSIONS:	18.8cm x 12cm x 2.6cm (7.4" x 4.7" x 1.0") W, D, H, 1/2 19" 1U
WEIGHT:	0.41kg (0.9lbs) approx.
SHIPPING DIMENSIONS:	35.1cm x 21.2cm x 7.2cm (12.4" x 8.4" x 2.8") W, D, H.
SHIPPING WEIGHT:	0.95kg (2.1lbs) approx.
INCLUDED ACCESSORIES:	Power supply.
OPTIONS:	RK-T2B 19" rack adapter.