

NTI e-5d-48v Medium Enterprise Environment Monitoring System/48VDC Power

RJ45 Sensor Ports

- Five RJ45 modular jacks for connecting NTI temperature, humidity, temperature/humidity, liquid detection, smoke detection, glass break, vibration and motion sensors.
 - Two levels of user-defined alerts – non-critical and critical.
- Provides +12 VDC, 100 mA for each port

Digital Inputs

- Five screw terminal pairs for connecting dry contact devices.
- Potential-free
- Input voltage: 0VDC to +25VDC
- Over-voltage surge protection
- Maximum resistance to close contact: 300K Ohm

Output Relays

- Two screw terminals pairs.
- Potential-free relay switch contacts.
- Normally open / normally closed connection points.
- Maximum switching load: 0.5A at 125VAC, 1A at 30VDC, 0.5A at 48VDC.

Alarm Port

- One screw terminal pair.
- Provides +12VDC, 180 mA to supply an alarm beacon or siren.
- Fuse protection

AUX Power

- One screw terminal pair.
- Provides +12 VDC, 500 mA.

RS232 AUX Port

- One RJ45 port for connecting a serial GSM modem or a remote serially-controlled device.

USB Device Ports

- Four female USB Type A connectors for connecting USB modem or for downloading log data to USB flash drive.

USB Console Port

- One female USB Type B connector for connecting a PC for serial terminal access.

Ethernet Port

- One 10/100 Base-T Ethernet port with RJ45 Ethernet connector.
 - Supports full- and half-duplex.

Power

- Dual DC power.
 - If the first power source fails, the unit will automatically, without interruption, switch over to the second power source before switching to the optional battery backup.
- Input: 100 to 240 VAC at 50 or 60 Hz via AC adapter.
 - Includes one country-specific AC adapter. The second AC adapter is sold separately.
- Output: 9 VDC, 3A
- Power Consumption: 15W
- Use the PWR-48V-12V1-6A DC-DC power converter to install all other E-5D units in a 48V or 24V Telecom environment.
 - E-5DB-IND requires the PWR-48V-12V1-6A-55x25 DC-DC power converter
 - Optional 48VDC power.
 - E-5D-48V
 - Accepts 18~72VDC (48VDC nominal).
 - For installation in a 48V or 24V Telecom environment

MTBF

- E-5D-48V: 151,947 hours.

Protocols

- HTTP/HTTPS, SNMP V1/V2c/V3, SMTP, TCP/IP, Syslog, SNMP, DHCP, SSHv2, SSLv3, TLS, LDAPv3, XOAUTH2, AES 256-bit, 3DES, Blowfish, RSA, EDH-RSA, Arcfour, IPV6, WAP 2.0, RADIUS
 - Support for XOAUTH2 provides higher security authentication for email accounts (e.g. Gmail).
- Compatible with any SNMP management software.
 - The unit can be polled via SNMP.
- Operates and configures via HTTP/HTTPS web page, Telnet, SSH, or USB/RJ45 serial interface.
- An IP address can be assigned to the E-5D automatically by a DHCP server.
- Generates SNMP traps, email alerts, syslog messages, and SMS messages (via USB 3G modem).
 - Alerts are posted in event log, which is accessible through Web user interface.
 - Email alerts can be sent to 17 addresses.
 - Users can configure the schedule for when they will be alerted, as well as customize the e-mail subject line for each sensor alert.
 - SNMP traps have unique OID's (Object Identifiers) for each sensor.

Internal Temperature Sensor

- Applications from:
 - E-5D: 32 to 140°F (0 to 60°C), $\pm 0.72^\circ\text{F}$ ($\pm 0.40^\circ\text{C}$)
 - Accuracy:
 - $\pm 1.62^\circ\text{F}$ ($\pm 0.90^\circ\text{C}$) for -40 to 14°F (-40 to -10°C).
 - $\pm 0.72^\circ\text{F}$ ($\pm 0.40^\circ\text{C}$) for 14 to 185°F (-10 to 85°C).

Internal Humidity Sensor

- Applications from:
 - E-5D: 20% to 80% relative humidity at 32 to 140°F (0 to 60°C), $\pm 3\%$
 - Accuracy:
 - 15 to 80% relative humidity, $\pm 3\%$
 - 80 to 90% relative humidity, $\pm 4\%$

Dimensions

- E-5D-48V: 10.6x3.1x1.75 in (269x79x44 mm)

Regulatory Approvals

- CE, RoHS

Warranty

- Two years