

## TASCAM VL-S3 Two-way 3 inch Powered Monitor (pair)/80Hz - 22kHz

	<b>VL-S3</b>
Maximum effective output (distortion:10%)	14W+14W
<b>Speaker units</b>	
woofer	3"(76.2mm)
tweeter	0.5"(12.7mm)
Enclosure	Bass reflex type
Frequency response	80Hz - 22kHz
Crossover frequency	8kHz
Sensitivity	-4.8dBV(580mV) 14W+14W
External input jacks	RCA pin-jacks(stereo), 3.5mm(1/8") stereo mini jack
Input impedance	50k ohms
Power	Dedicated AC adapter(PS-P1524E)
Input voltage	AC100-240V, 50/60Hz
Output voltage	DC15V
Output current	2.4A
Power consumption	6.2W
Dimensions	110 (W) × 170 (H) × 138 (D) mm 4.3 (W) × 6.7 (H) × 5.4 (D) inches (not including projections)
<b>Weight</b>	
Active unit (left)	1.1kg / 2.4lb
Passive unit (right)	1.0kg / 2.2lb
Included Accessories	AC adapter (TASCAM PS-P1524E), Speaker cable, RCA-6.3mm(1/4") standard TS jack adapter cable, Owner's Manual (including warranty)