



## 12VDC Switching CCTV Power Supplies

### PS-U0406-PULQ

4 Outputs, Total supply current: 6A

### PS-U0906-PULQ

9 Outputs, Total supply current: 6A

### PS-U1806-PULQ

18 Outputs, Total supply current: 6A

### PS-U1812-PULQ

18 Outputs, Total supply current: 12A

The **ENFORCER**® DC Switching CCTV Power Supplies are a lightweight and efficient solution for powering CCTV installations. Each unit efficiently handles power and has built-in protection against short circuiting and overheating.



PS-U0906-PULQ

### Features:

- Universal 100~240 VAC input
- New lightweight, cost-effective design
- Each output individually fused (PTC-type fuses)
- Adjustable output to reduce voltage drop
- PTC fuses rated 2.5A@12.6~13.5 VDC
- Individual output status LEDs
- Heavy-duty steel case with removable cover
- Built-in short circuit and overheat protection
- 6-foot power cord included



PS-U1812-PULQ

### Specifications:

	PS-U0406-PULQ	PS-U0906-PULQ	PS-U1806-PULQ	PS-U1812-PULQ
Outputs	4	9	18	18
Total supply current	6A			12A
Max. current / output	2.5A			
Output fuse	PTC			
Output voltage	12.6~13.5 VDC			
Input fuse	Micro fuse 3.15A@250VAC			
Input voltage	100~240 VAC (50~60 Hz)			
Dimensions	10"x7 <sup>3</sup> / <sub>4</sub> "x3 <sup>1</sup> / <sub>2</sub> " (254x197x89 mm)			12 <sup>1</sup> / <sub>8</sub> "x12 <sup>1</sup> / <sub>4</sub> "x3 <sup>5</sup> / <sub>8</sub> " (308x311x92 mm)
Weight	5-lb (2.3kg)			8-lb 1-oz (3.65kg)

### SECO-LARM

16842 Millikan Ave • Irvine, CA 92606

Tel: 949-261-2999 / 800-662-0800 • Fax: 949-261-7326

sales@seco-larm.com • www.seco-larm.com



Copyright 2012 © SECO-LARM U.S.A, Inc. All rights reserved.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

**SECO-LARM ENFORCER® CRIMEBUSTER® CBA SLI**

pi-PS-Uxxx-PULQZZ