

NTI e-1wp Environment Monitoring System with 1-Wire Sensor Interface over Ethernet (PoE)

The ENVIROMUX® Environment Monitoring System (EMS) with 1-Wire Sensor Interface monitors critical environmental conditions, such as temperature, humidity, liquid water presence, power, intrusion, and smoke. When a sensor goes out of range of a configurable threshold, the system will notify you via email, web page, network management (SNMP), and/or SMS messages (via email-to-SMS).

The system supports 24 single reading 1-wire sensors in any combination – temperature, humidity, dew point, thermocouple or digital inputs – and 2 separate digital inputs. It functions independently or as an IP-connected remote sensor for the E-2D/5D/16D.

The ENVIROMUX® Environment Monitoring System (EMS) with 1-Wire Sensor Interface monitors critical environmental conditions, such as temperature, humidity, liquid water presence, power, intrusion, and smoke. When a sensor goes out of range of a configurable threshold, the system will notify you via email, web page, network management (SNMP), and/or SMS messages (via email-to-SMS).

The system supports 24 single reading 1-wire sensors in any combination – temperature, humidity, dew point, thermocouple or digital inputs – and 2 separate digital inputs. It functions independently or as an IP-connected remote sensor for the E-2D/5D/16D.

Features:

- Monitor and manage environmental and security conditions over IP.
- Sensors supported:
 - 2 digital inputs sensitive to contact closure.
 - 2 RJ11 6P4C connectors for daisy-chaining 1-wire temperature/humidity/dew point, thermocouple, or digital input expanders in any combination.
 - Up to 24 temperature, thermocouple, or any single reading 1-wire sensor can be connected between both RJ11 connectors.
 - Up to 8 temperature/humidity/dew point combination 1-wire sensors can be connected between both RJ11 connectors. Each temperature/humidity/dew point sensor is equivalent to 3 single reading sensors.
 - Up to 12 E-DI2-1W digital input expanders can be connected between both RJ11 connectors to allow a maximum of 24 additional digital inputs. Each E-DI2-1W is equivalent to 2 single reading sensors.
 - Maximum cable length supported on each connector is up to 600ft (183 m) depending on the configuration and number of connected sensors.
 - Use RJ11 splitters (RJ11-3JCK) to daisy-chain 1-wire sensors (sold separately).
- Sensors are hot pluggable.
 - The sensors will automatically be detected on power up or a Detect Devices button on the summary page can be selected when logged into the unit.
- Monitors (ping) up to 4 IP network devices - alerts are sent if devices are not responding.
- Sensor conditions can be configured to trigger alerts by themselves, and/or be used in combination with other alerts to trigger one Smart Alert.
- Supports 4 IP network video cameras for live view of any facility.
- Create multiple alerts for any installed sensor.
- Sensor conditions can be configured to trigger alerts by themselves, and/or be used in combination with other alerts to trigger one Smart Alert.
 - Configure up to 32 alerts, and one Smart Alert.
- Dual redundant power supplies for connection to two separate power sources.
 - The second power supply is sold separately.
- Available with optional Power over Ethernet (POE).
- Integrates with various Open Source SNMP monitoring packages – Nagios
 - The unit can be polled via SNMP.
- Optional intuitive graphical management software provides an easy-to-use, unified interface for both monitoring and configuring up to 3,000 ENVIROMUX units and all connected sensors.
- Security: HTTPS, SSLv3, AES 256-bit encryption, 16-character username/password authentication, user account restricted access rights.
- Ideal for a wide range of applications including IT infrastructure monitoring, cold storage/freezer monitoring, or any unmanned area that needs to be monitored.