

Shinybow SB-8188 8x8 VGA + Audio Matrix Switcher w/RS-232 and IR Remote

8x8 VGA + Audio Matrix Switcher w/RS-232 + IR Remote. Model SB-8188

The 8x8 VGA + Stereo Audio Matrix Switcher with RS-232 is designed to work as a switcher for multiple VGA sources and displays. Switch is controlled via RS232, IR Remote or Push Button on the front panel. A maximum bandwidth of 380MHz will support a sharp and highly defined video in multiple resolutions of up to 1920x1200. Because it is a matrix switcher, it allows any input to be routed to any output; or the same input to be routed to all outputs or any combination. It completely eliminates the need to constantly move around video input and output cables.

Features:

- Switches VGA Video between multiple sources and displays.
- Allows connection of 8 sources and 8 displays
- Supports resolutions up to 1920 x 1200
- Supports Stereo Audio Signal via 3.5mm audio inputs
- IR Remote Control
- RS232 Control (Software Included)
- Rack-Mountable (mounts included)
- Installs in seconds

Specifications:

- Video Amplifier Bandwidth: >380MHz
- Resolutions: up to 1920 x 1200
- Video Input Connectors: 8 sets of DB-15 (VGA or RGBHV)
- Video Output Connectors: 8 sets of DB-15 (VGA or RGBHV)
- Audio Inputs: 8 sets of 3.5mm Stereo jacks
- Audio Outputs: 8 sets of 3.5mm Stereo jacks
- Net Weight: 9lbs
- Power Consumption: 450mA (max.)
- Power Supply: 12VDC; 500mA~2000mA
- Dimensions: 17.32 " W x 7.8 " D x 4.02 " H

Package Includes:

- 8x8 VGA Matrix Switcher
- IR Remote
- Instruction Manual
- Rack Mounts
- AC/DC Adapter: 12VDC, 500mA~2000mA
- RS-232 driver CD (Windows 98/2000/XP only)

Warranty: 1 year labor/parts manufacturers warranty.