

## **Apantac OG-US-4000-SET-1 OG-US-4000-MB with OG-US-4000-RM/Occupies 2 slots in the openGear frame**

**BUNDLE: OG-US-4000-MB + OG-US-4000-RM. Occupies 2 slots in the openGear frame.**

### **OG-US-4000-MB**

openGear card. Universal Scaler with Genlock. Converts HDMI or SDI to HDMI and SDI with embedded audio. Supports any HDMI (up to 1920x1200) and SDI (up to 1080p) input resolution. SDI output can be set for 720P, 480i/P, 576i/P, 1080i/P at 23.98, 24, 25, 29.97, 30, 50, 59.94 and 60Hz. HDMI output can be set for 720p, 480i/p, 576i/p, 1080i/P at 50/60Hz.

### **Features**

- openGear 3.0 card-based form factor
- Supports HDMI and SDI inputs
- Supports HDMI and SDI outputs
- Supports Genlock
- Scale any SDI input resolution to HDMI and SDI
- SDI output supports 720p, 480i/p, 576i/p, 1080i/p
- SDI output frequency in 23.98, 24, 25, 29.97, 30, 50, 59.94, 60Hz
- HDMI output supports 720p, 480i/p, 576i/p, 1080i/p
- HDMI output frequency in 50, 60Hz
- Low power consumption - 15W
- 5 year limited warranty

### **OG-US-4000-RM**

openGear Rear Module for OG-US-4000-MB. Occupies 2 slots in the openGear frame. 1 x HDMI input, 1 x SDI input BNC, 1 x SDI output BNC and 1 x HDMI output.