

SWIT CM-55C 5.5 inch Full HD 4K-HDMI LCD Monitor

The CM-55C adopts a 5.5-inch LCD panel with LED backlight, The native resolution is Full HD 1920x1080, contrast 1000:1, brightness 450nit, and viewing angle is Horizontal/Vertical: 178°

Input/Output Interfaces

4K-HDMI

CM-55C monitor supports:

HDMI 1.4 (4K30p) input × 1

3.5mm audio output × 1

SD card input for 3DLUT upload and Firmware upgrade

Single Joystick Operation

The monitor operation can be easily realized by only one Joystick:

Up: Quick Zoom-in mode

Down: Cancel / Delete current scene

Left/Right: Preset Scenes switching

Long Left: Enter Menu system

Long Right: Add a new scene

Press down: Edit tools in current scene / Confirm settings

Quick Zoom-in and Pan

Scroll the joystick up, to zoom-in the image by 2x or 4x; and during zoom-in mode, press the joystick, you can easily pan the image up/down/left/right by the joystick.

Scene Layout Edit and Switch

Different from the traditional multi-buttons monitors, the CM-55C adopts the preset scenes and switching operations. You can add up to 8 scenes, and add 8 function shortcuts to each scene. Scroll the joystick left / right to switch between the layout scenes easily, instead of complex menu buttons operations.

3DLUT Log to Rec709

User LUT cube import

CM-55C provides more than 20 De-log 3DLUTs, Includes S-log2/3, V-log, C-log1/2/3, Log-C, J-log1, RedLog, BMD, FujiFilm, GoPro, DJI etc, to convert log mode to REC709 for all major cameras.

User 3DLUT upload

User creative 3DLUT cube or calibration 3DLUT cube can be uploaded to CM-55C by SD card. Max 16 user 3DLUT can be restored.

Super False Color Exposure Assist

Besides normal spectrum false color, the CM-55C supports more powerful Super False Color mode, including under-exposure / Over-exposure / 18 degree grey / Skin tone indications, to help you to get a correct exposure easily.

Features

- 5.5-inch IPS LCD, 1920x1080 FHD
- HDMI 1.4 (4K30p) input
- 2x 4x Quick zoom-in and Pan
- Focus assist and precision adjust
- Waveform / Vector / Histogram
- Build-in 20+ De-log 3DLUTs
- User DIT 3DLUT import by SD card
- 2-ch HDMI audio meters display
- Super False color, Zebra stripes, Anamorphic
- Single joystick quick operation
- Battery slot for both NP-F & LP-E6