

SWIT S-8U95 98Wh Battery for Sony BP-U series

S-8U95 is the replacement battery for Sony BP-U60, complete compatible with Sony Camcorder PMW-EX1/EX3/F3/100/200/300, PXW-X160/180/200, PXW-FS7/FS5, and the latest PXW-Z190/Z280. S-8U95 can exchange digital info with the camera, and display remaining power info on the camera viewfinder.

98Wh / 6.8Ah High Capacity

With 14.4V nominal voltage, the S-8U95 has 98Wh/6.8Ah capacity, and can run approx 3.5 hours on Sony PXW-Z280 with LCD on.

Build-in D-tap DC Output Socket

A D-tap DC output socket is equipped on the side of S-8U95 battery, for DC 14.4V (nominate) connection. You can connect on-camera LED light, monitor or wireless transmitter on the D-tap socket, and get power simultaneously with camera. The Max power from D-tap is 50W, 3.5A. The D-tap socket can also be used as charging input, by SWIT portable charger PC-U130B/B2. (For FS7, S-7105 90° connector is required).

4-level LED Power Indicator

The S-8U95 battery has the 4-level LED power indicators to check the battery remaining capacity. You can get a quick view of capacity before using. The "Check" button can also be used to trigger USB charging.

Easy Charging

The S-8U95 can be charged by SWIT 2-ch charger S-3602U, 4-ch charger LC-D421, or SONY original charger BC-U1 single channel charger. It will take about 4 hours and 20 minutes to reach fully charged.

And it also can be charged via D-tap port by SWIT PC-U130B/B2 D-tap Charger. It will take 2 hours 50 minutes for complete charge.

Features

- Li-ion battery pack of 14.4V nominal voltage ■
- Complete compatible with Sony PMW-EX1/EX3/F3/100/200/300, PXW-X160/180/200, PXW-FS7/FS5 and the latest PXW-Z190/Z280. ■
- Display remaining power info on camera viewfinder ■
- 98Wh / 6.8Ah capacity ■
- 4-level LED power indicator ■
- 14.4V D-tap DC output ■
- 5V/1A USB charging output ■
- Multiple circuit protections