

## PreSonus PM-2 Stereo Pair of Small-Diaphragm Cardioid Condenser Microphones

|                        |                                                                |
|------------------------|----------------------------------------------------------------|
| Capsule Type           | 19mm, gold sputtered 6 micron Mylar, small-diaphragm condenser |
| Preamp Type            | Class A FET                                                    |
| Sensitivity            | 8 mV/Pa                                                        |
| Frequency Response     | 40 Hz to 18 kHz                                                |
| Polar Pattern          | Cardioid                                                       |
| Equivalent Noise Level | 22 dB SPL A-wtd                                                |
| Maximum SPL            | 135 dB                                                         |
| Total Load Impedance   | -1 k $\Omega$                                                  |