

Electro-Voice RE3ACCRFAMP Active RF Antenna Booster/470-960MHz

Carrier frequency:	470 - 960 MHz
RF connectors:	BNC
Antenna gain:	1.8dBi
Booster gain:	10dB (± 2 dB)
Coverage angle:	360 degrees
Operating voltage:	+8 to +12v DC
Usage:	Indoor or outdoor (not waterproof)
Dimensions (length):	3.03" (77mm)
Dimensions (height):	2.07" (52.5mm)
Dimensions (depth):	0.7" (18mm)
Finish:	Polyurethane paint, black
Net weight:	6.95 oz. (197 g)
Gross weight:	9.17 oz. (260 g)