

Current Audio AX-1250DAV 8 Zone/12 Source Multi-Room Controller with Amplifier

- 55 Watts per channel @8Ω (4Ω capable for 3 zones)
- Local mobile device music playback (iOS and Android) and UPnP push functionality
- Fully implemented UPnP server
- Auto zone On/Off via source audio sensing
- Expandable to 96 zones (via network expansion)
- Bass, Treble, Balance and Loudness per zone
- 12 Audio Sources:
 - S1 - 8 either Analogue, or Digital Coax (PCM)
 - S9 - 12 either Digital Coax or Optical (PCM)
- S13 - Ethernet/Internet stream. HD audio and Compression free formats supported
- Up to 10 seconds of 44.1 KHz 16 Bit stereo audio for the doorbells
- 10 Buffered IR outputs
 - 1 - 8 routing
 - 9 - 10 summed
- Internal Web Page with user access control and setup
- iOS and Android compatible via FREE app
- Keypad/IR connection for every zone
- Control4 driver available - FREE (net and UPnP function not supported)