

Datavideo SE-650 4 Input HDMI/HD-SDI Digital Video Switcher with Built-In Audio Mixer

Interfaces	
Video Inputs	2 x HDMI 2 x HD-SDI
Video Outputs	2 x HDMI (HDMI 1 is user assignable / HDMI 2 is Multiview) 1 x HD-SDI (User assignable)
Audio Inputs	1 x Stereo RCA (L/R) 2 x Mono Microphone De-embedded Digital Audio (2 CH)
Audio Outputs	1 x Stereo RCA (L/R) 1 x Stereo headphone (Mini Jack with volume control) Embedded Digital Audio (2 CH / Channel 1 & 2)
Tally	Yes / D-Sub 15 male connector
Software Update	USB Port
Audio Mixer	
Audio Fader	5 VR (Variable Resistor) 6 Channel (3 Pair) Audio Mixer
Audio LED Meter	2 Rows (Left/Right)
Standards	
Supported Resolutions	1080i/50, 1080i/59.94, 1080i/60, 720p/50, 720p/59.94, 720p/60
Internal Processing	YUV 4:2:2 10-bit
Extras	
Keyers	2 Keyers (2 Chroma Keyers); linear and luma keyer
Upstream Keyers	2 (M/E Keyer & PIP)
Chroma Keyers	2 High Quality Chroma Keyers; available in Keyer and PIP
PIP	1 x PIP with adjustable size, position, and crop. Border with adjustable width & color
Wipes	32 Wipe Patterns such as Circle and Heart. Variable border width with Softness control.
Stills	Any unused channel can also be used as a still buffer. Stills can be stored internally
Stinger Transitions	Yes
Logo	1