

Model Name	SE-1200MU
Product Name	HD 6-Channel Digital Video Switcher
Video Standard	HD
Video Format	1080i 50/59.94/60Hz 720p 50/59.94/60Hz
Video Processing	SDI: 4:2:2 HDMI: YUV 4:2:2 10 bit, RGB 4:4:4
Input Routable / Crosspoint	All 6, repeatable
Video Input	4x HD-SDI 2x HDMI (RGB/YUV, 1080i/1080p/720p)
Mix HD & SD source	N/A
Computer Graphic Interface	2 via HDMI
Video output	2x HD-SDI & 2x HDMI assignable: PGM(w/DSK 1&2), PGM(w/DSK 1), PGM Clean, PVW(w/o DSK), multi-view, Input 1-6
Down-converted output	N/A
Built-in Multi-view monitoring out	HDMI & Ethernet (MJPEG)
Audio input	2x Balanced XLR
Audio output	N/A
Embedded audio support	embedded 2-CH audio output from XLR input
Audio Delay Calibration	N/A
A+V switching	N/A
Chromakey	2 Keyers
Title Creator	N/A
USK	2x USK support Chromakey & Linear / Luma Key
DSK	2x DSK support Lumakey & Linear key (Key / Fill)
Picture in Picture	1
Logo Insertion	N/A
Still Store	1000+

Effects	FTB, Cut, 32 Wipe with border
Transition Preview	Full transitions preview
Sync / Reference In/Out	Built-in Genlock (internal)
Tally Output	1x D-sub 15pin, dual color
PC Remote Control	Via Ethernet (free Window software) or RS-232
Built-in Audio Mixer	N/A
Special Features	Motion JPEG Multi-view streaming (120 memory preset, BGD Transition on/off option) Stinger transition
Chassis	1RU Rack-mount
Power	DC 12V 30W
Accessory	CB-46/47/50 (30/50/100m)