

Video Distribution Amplifier

Description

The SB-3706 series are 1in to 8out of Video or S-Video(Y/C) Distribution Amplifier. They are one of the most innovative Video/S-Video distribution product. They are distribution of signals included S-Video(Y/C),Video(Composite Video). These products provide multiple 8 outputs that are identical to the source signal. There are useful for distributing signals from VCRs, Camcorders, Video Game Consoles, DVDs, Satellite Receivers, CATV Set Top Boxes, etc.

* SB-3706 use Composite Video, SB-3706SV use the S-Videos(Y/C)

1x8 Composite Video (RCA)

SB-3706



Front View :



Rear View :



Video Input : 1x Composite Video(RCA)
Video Output : 8x Composite Video(RCA)

1x8 Composite Video (BNC)

SB-3706BNC



Front View :



Rear View :



Video Input : 1x Composite Video(BNC)
Video Output : 8x Composite Video(BNC)

1x8 S-Video(Y/C)

SB-3706SV



Front View :



Rear View :



Video Input : 1x S-Video(Y/C)
Video Output : 8x S-Video(Y/C)

Features

INPUT :

Video system :	SB-3706	Composite Video
	SB-3706SV	S-Video(Y/C)
Video Input :	0.50Vpp ~2Vpp, 75 Ω	
Input Terminal :	SB-3706	RCA Connector
	SB-3706BNC	BNC Connector
	SB-3706SV	Mini-din 4 pin

OUTPUT :

Video system	SB-3706	Composite Video
	SB-3706SV	S-Video(Y/C)
Video Output	1 Vpp, 75Ω	
Output Terminals	SB-3706	RCA Connector
	SB-3706BNC	BNC Connector
	SB-3706SV	Mini-din 4 pin

Video Bandwidth	250MHz, +/- 3db
Video Distortion	>1.2db
Power Consumed	@ 350mA Maximum
Power source	DC 12V,@500mA

Installing;

APPLICATIONS :

1. VCDs
2. VCRs
3. DVDs
4. STBs
5. Satellite Receivers



DC INPUT AVAILABLE:
DC 12V , @500mA



8 Video Converter
Item : SB-3706

