

Vaddio 999-5655-000 ProductionVIEW HD-SDI MV All-in-One Camera Control Console with Video Switching/Mixing

Part Numbers:	999-5655-000 (North America) 999-5655-001 (International)
Compatible PTZ Cameras:	Vaddio, Panasonic & Sony (cameras require optional SDI card)
Video Switcher:	6 Inputs x 2 Outputs - OR - Two (2) Independent 6 x 1 Switchers in Dual Mode
Video Transitions:	Crossfade, 9-wipe options and straight cuts, fade to black with a selectable transition time of .01 to 4.0 seconds
Video Inputs:	Five (5) HD-SDI/SDI inputs on BNC connectors One (1) DVI-I Input (DVI-D, RGBHV, YPbPr, HDMI (DVI1.0 and HDMI 1.3 Compliant Receiver)
Preview or Multiviewer Outputs:	One (1) Preview output BNC-F for HD-SDI or SDI Two (2) Preview or Multiviewer Outputs (HDMI)
Program Output:	One (1) Program output BNC-F for HD-SDI or SDI One (1) Program output (HDMI) Note: Transitions only appear on the Program outputs
External Reference:	One (1) BNC-F Input for External Reference (sync)
Camera Control Ports:	Six (6) RS-232 on RJ-45-F
Control Interface:	One (1) RS-232 on DE-9-F (DB-9-F)
8-Line LCD Display (Menu):	Eight (8) line backlit LCD display
Power Requirements:	18 VDC, 2.78 Amp Switching Power Supply
Control Inputs for Auto Mode (input 1 & 2):	Cameras 1 & 2 have 6 presets each or Camera 1 can have 12 presets (Select between Trigger Inputs for Camera Presets or Tally Outputs)
Tally Output:	Tally outputs for each of the six video inputs (Select between Trigger Inputs for Camera Presets or Tally Outputs)
Weight (approximate):	9.5 lbs. (4.32kg)
Dimensions (W x D x H):	16" (40.64cm) x 10" (25.4cm) x 4" (10.16cm)