

## Bosch INT-TX32 Digital 32-Channel Extender (Transmitter) with Optical Link

Mains voltage	100-240 Vac, 50-60 Hz
Power consumption	
operating, maximum	55 W
standby	29 W
Asymmetrical audio inputs	from -6 dBV maximum @ +6 dB gain till +6 dBV maximum @ -6 dB gain
Symmetrical audio inputs	+6 dBV maximum @ +6 dB gain+18 dBV maximum @ -6 dB gain
Emergency switch connector	Emergency control input
Headphone output	32 ohm to 2 kohm
HF input	Nominal 1 Vpp, minimum 10 mVpp, 75 ohm
HF output	1 Vpp, 6 VDC, 75 ohm
Dimensions (H x W x D)	
for tabletop use, with feet	92 x 440 x 410 mm(3.6 x 17.3 x 16.1 in)
for 19" rack use, with brackets	88 x 483 x 410 mm(3.5 x 19 x 16.1 in)
in front of brackets	40 mm (1.6 in)
behind brackets	370 mm (14.6 in)
Weightwithout brackets, with feet	6.8 kg (15.0 lb)
Mounting	Brackets for 19" rack mounting or fixing to a tabletopDetachable feet for free-standing on a tabletop
Color	Charcoal (PH 10736) with silver