

# **Adder X100/R-US KVM Extender (Receiver) for PS/2 computers up to 100m/330ft**

## **Video resolutions**

1600 x 1200 at distances up to 100m/330ft, 1900 x 1440 at distances up to 50m/165ft

## **Extension distance**

Up to 100m/330ft using CATx cable (x=5,5e,6,7)

## **Devices supported**

Supports any computer with PS/2 or USB style keyboard and mice, flat-screen and CRT style monitors with standard HD-15 video connectors and optional audio through 3.5mm audio jack

## **O/S compatibility**

All known software and operating systems including Windows (all), DOS, Linux, Unix, BSD, Sun OS, Solaris, Mac OS, NetWare etc.

## **Connectors (local)**

Video: HDD15 Keyboard Mouse: MiniDin6. Optional audio: 3.5mm jack CATx: 1 x RJ45 connector Or Video: HDD15 Keyboard Mouse: USB type A. Optional audio: 3.5mm jack CATx: 1 x RJ45 connector

## **Connectors (remote)**

Video: HDD15 Keyboard Mouse: MiniDin6. Optional audio: 3.5mm jack CATx: 1 x RJ45 connector. Power: 2.5mm DC jack

## **Physical (local)**

Combination of plastic enclosure and cables. Enclosure: 64mm x 45mm x 25mm Cables: 340mm long

## **Physical (remote)**

All metal case, 123mm x 74mm x 26 mm

## **Power supply**

100 - 240VAC 50/60Hz

## **Operating temperature**

0 - 40 deg C (32 to 104 deg F)

## **Approvals**

CE, FCC