



MODEL #	VZ-MV401
SPECIFICATIONS	
HDMI® signals with Deep Color and HDCP	1.4 / 2.2
Input Resolution	Up to 4K@60Hz, 4:4:4 Color Sampling
Output Resolution	Up to 4K@60Hz, 4:4:4 Color Sampling
Scaling	Up to 4K@60Hz, 4:4:4 Color Sampling
PIP & POP	Support
Custom Layout	14 Layout (6 preset & 8 custom)
Rotation	Support (R 90° & L 90°) - On 1080p Input
Flip	Support
RESOLUTION	
Video Output	4096 x 2160@60Hz, 4:4:4 Color Sampling
INTERFACE	
HDMI Input	4 ea
HDMI Output	1 ea
Audio R/L	1 ea
USB 2.0	1 ea - Firmware
Serial Port (RS-232)	1 ea
Network (RJ-45)	1 ea - 10/100/1000 Base-T
WEIGHT & DIMENSIONS	
Dimensions (W x D x H)	17.33" x 9.05" x 1.77" / 440.4 x 230 x 45 mm
Net Weight	5.99 lbs / 2.72 Kg
MOUNT	
Server Chassis	1U (19")
GENERAL	
Transmitter - IR Remote Control	YES
Power Electrical Ratings Consumption	DC 12V/2A, locking barrel connector 15W
Operating / Storage Temperature	32 ~ 113°F (0 ~ 45°C) / -4 ~ 140°F (-20 ~ 60°C)
Operating Humidity	20 % ~ 90 % RH
LED Indicator Color	Input, Layout, Input Swap, Lock - Blue Standby On - Red Standby Off - Green

VZ-MV401 ADVANTAGES

- Fast switching among input channels and combined multiple images on single monitor
- Handles HDMI® signals with Deep Color and HDCP 1.4 / 2.2
- Supports input/output resolution up to 4K@60Hz, 4:4:4 color sampling
- Supports scaling up to 4K@60Hz, 4:4:4 color sampling
- Supports 14 screen layouts - 6 preset and 8 customized screen layouts
- Rotation (R90° and L90°) when input resolution up to 1080p or flip output in full screen layout
- Receives Dolby Digital® 5.1, DTS® 5.1 and uncompressed 7.1 linear PCM audio includes stereo analog audio input
- Supports front panel button, IR remote control, RS232 and Web UI
- Supports stereo audio output

INTERFACE




- | | |
|--------------|--------------|
| 1. HDMI OUT | 5. RS 232 |
| 2. HDMI IN | 6. USB |
| 3. AUDIO OUT | 7. DC 12V IN |
| 4. ETHERNET | 8. POWER |

Contact ViewZ


- Address : 177 W. Orangethorpe Ave., Placentia, CA 92870
- Phone : (714) 996-1177, Fax : (714) 996-1138
- Sales : sales@viewzusa.com
- Specification subject to change without notice.

Available Layout Presets


- Support PIP & POP
- Custom Screen Layout : Maximu 8 sets
- Preset Screen Layout : 6 presets




Preset 1




Preset 2




Preset 3



Preset 4



Preset 5



Preset 6

VZ-MV Cable Connection

