

Niles VCS100K Stereo Volume Control with Selectable Impedance

- Mounting Depth Of Only 2-9/16". Fits Into Standard 18-cubic-inch One-gang Junction Boxes.
- Power Handling: 100W/channel RMS.
- Frequency Response: 20Hz To 20kHz \pm 2dB.
- May Be Used With 4-, 6-, Or 8-ohm Speaker Systems.
- Installation Requires Only A Screwdriver And Wire Stripper.