

PureLink MPX-100 II HD WiFi Network Digital Signage Player with MPX Software

General Specifications	
Platform	Non-PC based , RISC or Embedded based platform, Android 4.4
Video Output	HDMI (1080P), VGA (720P)
Audio Output	RCA L / R jack, SPDIF digital audio jack
Supported Resolutions	up to 1080p@60Hz
Storage	16G SD card included (supports up to 128G)
Processor	ARM Cortex-A9, Quad-core 1.6G
Memory	DDR-3, 1G
NAND	8G EMMC NAND
Network	10/100 Mbps Fast Ethernet
Power Supply	AC 220V/50Hz
Power Consumption	12W
Operating Temperature	0~70°C
Storage Temperature	-20°C~80°C
Relative Humidity	10% ~ 85%
Audio Formats	MP3, WMA, WMA Pro, AAC, MPEG1/2 Layer ½, ADPCM, OGG Vorbis, Dolby Digital AC3, Dolby Digital Plus, RA-COOK, FLAC
Image Formats	JPEG, BMP, GIF, PNG, TIFF
Supported Media	
Media Type(s)	Video, Audio, Picture, Scrolling Text, Webpage, Weather, Date, Clock, Weather, Tags
Picture Mode	Portrait mode, background picture, multiple zone display
Video Formats	MOV, AVI, MP4, DVD, ASF, WMV, MKV, RM, RMVB, TS, DAT, MPG, MPEG, VOB
Audio Formats	MP3, WMA, WMA Pro, AAC, MPEG1/2 Layer ½, ADPCM, OGG Vorbis, Dolby Digital AC3, Dolby Digital Plus, RA-COOK, FLAC
Image Formats	JPEG, BMP, GIF, PNG, TIFF
Subtitles	Adjustable font, speed, size, color, and rolling mode
Enclosure	
Enclosure Type	All metal, black powder coat finish
Rack Mounting Option	Standard 19 inch rack-mountable design