

SECO-LARM PC-U1810-PULQ 12VDC Switching CCTV Power Supply/18 Outputs/10A total

| | |
|-------------------------|--|
| Outputs | 18 |
| Total supply current | 10A |
| Max. current per output | 1.1A |
| Output fuse | PTC |
| Output voltage | 11.0~13.8 VDC (adjustable by trimpot, $\pm 10\%$ (47~63 Hz)) |
| Input voltage | 100~220 VAC $\pm 10\%$ (47~63 Hz) |
| LED indicators | Cover -Green: AC Input, Red: DC Output PDM -Red: DC Output |
| Operating humidity | 90% (non-condensing) |
| Operating temperature | 32°~104° F (0°~40° C) |
| Dimensions | 10"x10-5/16"x3-1/8" (254x262x79 mm) |
| Weight | 5-lb 2-oz (2.31kg) |