Galaxy Audio GT-INST-6 2.4GHz Portable Wireless Extender (Transmitter/Receiver) System with Violin Mic

| GT-INST-6 SYSTEM | |
|-----------------------------|--|
| Frequency Range: | 2.4GHz Frequency Hopping |
| Frequency Response: | 20Hz - 20KHz |
| Pairing: | Auto-Match |
| Included Accessories: | Detachable Belt Clip, Cell Phone Adapter Cables (Black-iPhone and Red-Android), 1/8" to 1/4" Adapter, USB Charging Cable, 19.7" Female to Male Extension Cable, Windscreen, Rubber Shock Bracket |
| VIOLIN MICROPHONE | |
| Mic Diameter: | 0.1" x 0.24" (2.7 x 6 mm) (LxDia.) |
| Polar Pattern: | Omni-Directional |
| Sensitivity: | -46dB ±2dB |
| Frequency Response: | 196Hz - 12kHz |
| Standard Operating Voltage: | 2.0V - 10V.DC |
| Signal to Noise Ratio: | >58dB |
| Impedance: | ≤680Ω |
| GT- | TINST TRANSMITTER |
| Controls: | On/Off Power Switch, Volume Control |
| Battery: | Lithium-Ion Rechargeable |
| Input: | Mini USB for Charging |
| Indicators: | Power and Pairing |
| GT-R RECEIVER | |
| Controls: | On/Off Power Switch |
| Battery: | Lithium-Ion Rechargeable |
| Input: | Mini USB for Charging |
| Output: | 3.5mm Stereo Output Plug |
| Indicators: | Power and Pairing |