

# JACKS in the BOX

**JIB/BT4R**

## ***Wireless XLR Bluetooth® Receiver***

The JIB/BT4R is a lightweight, compact, portable XLR Bluetooth® receiver that allows a user to transmit high quality mono Bluetooth® audio wirelessly from a smart phone to an active speaker or mixing console. The receiver offers a practical, straightforward audio solution for venues that require a quick wireless set up. Just pair the receiver to a Bluetooth® enabled device such as a smart phone and plug it into an active speaker or mixing console. Using the JIB/BT4R eliminates cable clutter for a clean, hassle free set up.

The rechargeable receiver enlists an internal 3.7V Lithium battery and comes standard with a micro USB charging cable that can be plugged into a computer or A/C adapter to charge. For a more permanent mixer installation, it can stay plugged in for a continuous power source.

DJs accepting requested songs that they might not have in their track list can allow a user to Bluetooth® a song straight to their mixing console for live DJ mixing. Singers and musicians can stream audio wirelessly to the receiver while using another mic input for vocals. The JIB/BT4R can also be used for a number of other audio streaming applications including dance studios, aerobics classes, school and gym classes, house of worship, karaoke, weddings, and many more.

### ***JIB/BT4R***

- Bluetooth Receiver
- Transmit Audio from Phone to Active Speaker or Mixer
- Lightweight, Compact, & Portable
- Micro USB Rechargeable



## ***Dual Receiver Stereo Playback System***

**JIB/BT4RS**

The JIB/BT4RS system comes with two receivers to create a stereo-link. After pairing a phone to a receiver via Bluetooth®, a second receiver can be linked to the first receiver to work in tandem. This turns audio transmission into a stereo playback to better fill a room with more sound. Both receivers can then be plugged into two XLR inputs on a mixing console, and be outputted to two active speakers or amplifiers.

### ***JIB/BT4RS***

- Bluetooth Receivers
- Transmit Audio from Phone to Active Speaker or Mixer
- Dual Receivers for Stereo Playback
- Lightweight, Compact, & Portable
- Micro USB Rechargeable



MAKERS OF THE ORIGINAL  
HOT SPOT PERSONAL MONITOR



# JACKS in the BOX

## JIB/BT4R

### Specifications:

#### JIB/BT4R

**Bluetooth® Version:** V4.0

**Frequency Range:** 2.4GHz - 2.48GHz

**Input Connector:** Micro USB Charging Input

**Output Connector:** XLR/M

**Controls:** Power, PAD Switch, Bluetooth Pair/Stereo-Link Button

**Indicators:** Charging LED, Stereo-Link/Pair LED

**Sensitivity:** -80dBm < +/-0.1% BER

**Signal to Noise:** >75dB

**Total Harmonic Distortion:** <0.1%

**Operating Range:** Under Typical Conditions 32.8' (10 m)

Note: actual range depends on RF signal absorption, reflection, interference, and battery characteristics

**Operating Temperature:** Range -40° F to 176° F (-40 C° to +80 C°)

Note: battery characteristics may limit this range

**Dimensions:** 4.9" x 1.32" x 1.1"

(124 x 33.4 x 27.5 mm)(HxWxD)

**Weight:** 3.35 oz (95 g)

**Power Requirements:** Internal 3.7V Rechargeable  
Lithium Battery Power Supply

**Battery Operation:** About 10 hours



### JIB/BT4R Receiver



TOP CHARGING INPUT VIEW



BOTTOM XLR INPUT VIEW



FRONT VIEW



BACK VIEW



Specifications subject to change without notice.



MAKERS OF THE ORIGINAL  
HOT SPOT PERSONAL MONITOR

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 [www.galaxyaudio.com](http://www.galaxyaudio.com)  
Distributed in Canada by Audio Distributors International (ADI) 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada  
450.449.8177 FAX 450.449.8180

V20190208