

## Galaxy Audio JIB/BT4RS Dual Bluetooth Extender (Receiver) Stereo Playback System with XLR output

<b>Bluetooth® Version</b>	V4.0
<b>Frequency Range</b>	2.4GHz - 2.48GHz
<b>Input Connector</b>	Micro USB Charging Input
<b>Output Connector</b>	XLR/M
<b>Controls</b>	Power, PAD Switch, Bluetooth Pair/Stereo-Link Button
<b>Indicators</b>	Charging LED, Stereo-Link/Pair LED
<b>Sensitivity</b>	-80dBm < +/-0.1% BER
<b>Signal to Noise</b>	>75dB
<b>Total Harmonic Distortion</b>	<0.1%
<b>Operating Range</b>	Under Typical Conditions 32.8' (10 m) Note: actual range depends on RF signal absorption, reflection, interference, and battery characteristics
<b>Operating Temperature</b>	Range -40° F to 176° F (-40 C° to +80 C°) Note: battery characteristics may limit this range
<b>Dimensions</b>	4.9" x 1.32" x 1.1" (124 x 33.4 x 27.5 mm)(HxWxD)
<b>Weight</b>	3.35 oz (95 g)
<b>Power Requirements</b>	Internal 3.7V Rechargeable Lithium Battery Power Supply
<b>Battery Operation</b>	About 10 hours