

# Galaxy Audio AS-1400T Wireless In-Ear Personal Monitor/Extender (Transmitter)/40Hz-16kHz

AS-1400 TRANSMITTER	
<b>Main Frame Size</b>	EIA STANDARD 1/2 U
<b>Modulation Mode</b>	FM Stereo Modulation
<b>RF Output</b>	30 mW
<b>Max Audio Input Level</b>	+6dBV
<b>Gain Adjustment Range</b>	33dB
<b>Audio Input</b>	Line Level X 2, XLR/ 1/4" Combo Jack
<b>XLR Input</b>	Balanced Pin 1: Ground (cable shield) Pin 2: Audio + Pin 3: Audio -
<b>Audio Output</b>	1/4" Headphone Out
<b>Dimensions</b>	1.7" x 8.2" x 7.1" (44 x 209 x 180 mm)(HxWxD)
<b>Weight</b>	37.4 oz (1,060 g)
<b>Power Requirements</b>	12-18 V DC at 300 mA supplied by external power supply