

## TASCAM TM-180 Studio Condenser Microphone/20Hz - 20000Hz

Model	Condenser
Directivity	Cardioid
Frequency response	20Hz - 20,000Hz
Output impedance	200 $\Omega$
Load impedance	>1k $\Omega$
Sensitivity	-35dB +/-2dB (0dB=1V/Pa at 1kHz)
Max. SPL	130dB
S/N ratio	79dB
Connector	3 pin XLR, Male
Phantom power	48V
dimensions	50(W) x 190(H) x 50(D) mm
Weight	420g (Microphone body only)
Accessory	Suspension shockmount (Screw dia. 5/8 inch), hard case, Soft case, 5/8 to 3/8 conversion adapter