

# SECO-LARM E-931-S45RRQ 45Ft Reflective Photoelectric Beam Sensor

Type	NIR Reflective
Current Draw	Standby- 70mA@12VDC, Active- 55mA@12VDC
Sensing Range	0.5' to 45' (0.1 - 14m)
Operating Voltage	12~250 VAC / VDC
Reaction time	5ms~100ms adjustable
Light Source	IR LED
LEDs - Red	Trigger
LEDs - Yellow	Alignment
Output	SPDT Relay Output (NO/NC/COM)
Switching Capacity	3A@120VAC / 3A@30VDC
Operating Temperature	-4■■■~131■■■ F (-20■■■~55■■■ C)
Enclosure	IP66 Waterproof