## SECO-LARM E-9660-8B25 60.13ft IR Curtain Sensors for Indoor/Outdoor Access Control

| Туре                  | IR Curtain Sensors for Indoor/Outdoor Access Control                           |
|-----------------------|--|
| Current Draw          | Standby- 102mA, Active- 92mA   |
| Number of Beams       | 8  |
| Sensing Range         | 25' (8m) outdoor, 50' (16m) indoor   |
| Operating Voltage     | 12~24VDC   |
| Reaction time         | 0.5~60 ms  |
| Detection System      | Simultaneous break of 2 adjacent beams or any single beam (programmable)       |
| LEDs                  | (On): powered, aligned properly, (Flash): when beam is broken, (Off): no power |
| Case material         | IP 65 / Aluminum alloy   |
| Output                | NO/NC relay output, 1A @ 12~24VDC  |
| Operating Temperature | -49■■~131■■ F (-45■■~55■■ C)   |
| Dimensions            | 60-1/8" x 1-5/16' x 7/8" (1530 x 33 x 22 mm) [Length x Width x Height]         |
| Hardware              | Mounting Bracket Included  |