

SECO-LARM PR-312S-PQ Stand-Alone Indoor Proximity Reader/up to 500 users

Operating Voltage	12VDC
Current Draw- Active	80mA @ 12VDC
Current Draw- Standby	60mA @12VDC
Transmit Frequency	125kHz (EM125)
User Card Read Range	6" (15cm)
Master Card Limit	1 card
Super User Card Limit	5 cards
User Card Limit	500 Cards (5 groups @ 100 users)
Outputs- Doorbell Relay	N.O. Dry contact, 1A@24VDC
Outputs- Lock Strike Relay	Fail-safe/fail-secure, 3A@16VDC (solid-state relay)
Outputs- Tamper Switch	N.C. Dry contact, 50mA@16VDC
Relay Time Delay	Timed output 1-60 s or Toggle Mode
Operating Temperature	-4■-158■ F (-20■-70■ C)
IP Rating	IP55
Dimensions	4-3/4"x2-3/8"x15/16" (120x60x23 mm)