

## Electro-Voice SR400 SoundMate 17-Ch Personal Extender (Receiver) with Backlit LCD Display/EDR

- **Display** : Backlit on/tuning indicator
- **Frequency Response** : 100Hz to 10kHz (+/-3dB)
- **Power Requirements** : 2 x AA batteries
- **Signal to noise ratio** : >60 dB
- **RF Carrier Frequency Range** : 72 to 76 MHz
- **No Of Channels** : 17
- **Type of Output** : 1 x 1/8-inch mini jack
- **Working Range (Approximately)** : 300 ft