

## Bellari PA550 3 Channel Preamplifier with RIAA Phono

- Gain:  
Line 16.4 dB gain @ 1kHz  
Phono 56.6 dB gain @ 1kHz
- Input Impedance: 22k line and 47k Phono
- Output Impedance: 8 to 600 ohms Headphone, 47 ohms RCA
- Frequency Response: 3Hz to 36kHz
- Equalization: RIAA +/- 1 dB, 14Hz to 23kHz
- THD: .005% @ 1KHz
- S/N Ratio: >94 dB unweighted
- Size: 5.5"w x 3.5"d x 1.25"h