

Bellari VP549 Phonograph Preamplifier with RIAA EQ

- I/ O Connectors: RCA, 1/8" TRS Stereo
- Gain: 41.51 dB gain @ 1kHz at the "0" setting 31.64 dB of gain at the "-10" setting 45.66 dB of gain at the "+4" setting
- Input Impedance: 47k ohms
- Output Impedance: 32 ohms Headphone, 470 ohms RCA
- Frequency Response: 3Hz to 36kHz
- Equalization: RIAA +/- 1 dB, 14Hz to 23kHz
- Rumble Filter: 20Hz
- THD: .02% @ 1KHz
- S/N Ratio: >94 dB unweighted
- PWR: 15 VDC
- Size: 5.5"w x 3.5"d x 1.25"h