

Smartavi HDC-IR-TXS-b IR CAT5 Extender (Transmitter) up to 1000ft/300m (Bi-directional IR)

IR EYE input	
BIR Frequency Range	100 MHz
Capture Distance	75 Ohm
Cable Connector	RCA, Female
IR Signal Indicator	75 Ohm
IR Emitter Output	
IR Frequency Range	Stereo Audio
Emitter Distance	20 KHz, 0 dB
Cable Connector	10K Ohm
IR Signal Indicator	RCA
Box	
Power Requirements	12VDC 1A dongle power up to 250 ft.
Cable Link	CAT5 568A or 568B
Mechanical	
Height	1.0 in. (35 mm.)
Width	2.5 in. (85 mm.)
Depth	2.5 in. (85 mm.)
Weight	0.25 lb. (0.9 kg.)
Power Requirements	5VDC 30mA