

Galaxy Audio AS-1810-4 1800 Series Wireless Personal Monitor Band Pack with EB10

This listing is for AS-1810-4 WPM Band Pack (Earbuds EB10) only. Use description below as a general reference.

The AS-1800-4 band Pack System is designed with features for the professional. The system Includes four receivers and one transmitter. It is designed to get the whole band wireless in one package. The AS-1800-4 will allow a band to send one stereo mix to 4 individuals. The body pack receiver is set up for a king. With 150mW's of output to the earbuds, the AS-1800R is sure to be plenty loud for any environment. The receiver has a squelch adjustment, stereo/mono switch, LCD display, button lock, and a Magnesium Alloy Construction.

An unlimited number of receivers may be added at any time.

Features:

- 4 Receivers Included
- Featuring Mixed Mono Mode
- 640 Selectable Frequencies / 32 Selectable Channels
- Backlit LCD (Displays Channel Number, Frequency, Name, Battery level of Receiver, L/R AF Input, Stereo/Mono and Lock)
- UHF Phase Locked Loop
- Stereo or Mono Transmission
- Multiple Receivers can be used with 1 Transmitter
- Naming Function
- 30/100 mW Selectable Transmitter Output
- Monitor Output
- Single Rack Mount Included
- 300' Rang

Band Pack System The 1800 Band Pack Systems makes it easy for any band to Get Personal. The system includes four receivers and one transmitter. It is designed to get the whole band wireless in one package. The AS-1800-4 will allow a band to send one stereo mix to 4 individuals (additional receivers may be purchased). Additional transmitters may be purchased at a later date to add mixes.

AS-1800T Transmitter

- Easy to Read LCD
- 2 - 1/4" Line Outputs (unbalanced)
- Volume Control
- Two XLR/1/4" Combo Inputs
- Naming Function
- 30/100 mW Selectable Transmitter Output
- Monitor Output
- Detachable BNC Antenna

AS-1800R Receiver

- True Diversity
- Magnesium Alloy
- Construction
- 45-18kHz
- Mixed Mono Mode
- Frequency Display
- Backlit LCD
- Volume Control
- Battery Level indicator
- 150 mW earphone output
- Button Lock
- Squelch adjustment
- Volume Knob
- Auto Mute
- Stereo/Mono Switch
- Dimensions: 4.25" x 2.59" x .86" (108 x 66 x 22 mm)(HxWxD)

The Mixed Mono feature allows performers to adjust the balance of the Left and Right audio signals sent from the transmitter right on the body pack. With Mixed Mono:

- The performers can have their vocals in Input 1 and the band mix in Input 2 and adjust the volume of each independently to create their own personal mix, or
- You can send two different monitor mixes from the board so each performer can decide which mix they want to hear on their belt pack.