

Shinybow ANI-88S 8x8 HDMI V1.3 3D MATRIX SWITCHER

ANI-88S is a true Matrix Routing Switcher for HDMI signals. It is an 8 HDMI inputs with 8 HDMI outputs. Because it is a matrix router, any input may be routed to any output; or the same input may be routed to all outputs or any combination. It completely eliminates the need to constantly move around HDMI cables. The ANI-88S is useful for Matrix signals from HDMI source devices (such as Blu-Ray, DVD, Personal computer, set top box, and satellite receivers, etc.) Control is provided via front panel buttons with LED readout, IR remote control or RS 232.

Features:

- 3D Enabled
- HDMI Matrix Switching between multiple sources and displays
- Allows connection of 8 sources and 8 displays
- Frequency bandwidth: 6.75Gbps (single link)
- Supports resolutions up to 1080p
- Supports all latest HDMI audio formats including Dolby TrueHD and DTS-HD
- HDMI 1.3
- HDCP compliant
- HDMI Boosters are installed on all the outputs to make sure that signal has no degradation on output cables up to 60ft
- Input source LED indicators on each output select.
- Ideal for home theater integration, conference room and retail stores.
- Compatible with all HDMI sources and displays.

Specifications:

- Supports high resolution input/output:
PC: up to 1920x1200 and
HDTV: 480i, 576i, 480p, 576p, 720p, 1080i and 1080p
- Supports 50/60Hz transfer (worldwide compatible)
- RS-232 control.
- IR Extender Output (3.5mm)
- IR remote control
- Rack Mountable - 4RU
- Power Supply: 24V DC/6.25A Universal
- Dimensions: 19" (W) x 15.16" (D) x 7" (H)
- Weight: 19.8 Lbs
- Installs in seconds

In the box:

- ANI-88S HDMI Matrix Switch
- 24V Power Supply Adaptor (110/240V) and Power Cord
- Operation Manual
- IR Remote
- Rack mount bracket