# Adder AV108MP AdderView Multi Platform Single-User KVM Switch

#### **DESCRIPTION:**

Designed to control mixed PC, Sun, Mac and laptop computers from a single console, the AdderView 108 MP's range of popular features make it a good choice for PC only applications too.

The AdderView 108 MP is designed for demanding applications where reliable operation is needed across multiple computers and mixed operating systems and is a top choice with system administrators. USB keyboard support enables you to choose the optimum PC, Sun or Mac style keyboard to control your computers. Whatever the application, the 108 MP is a switch that will not disappoint.

#### **FEATURES:**

- Sun, PC and Mac style USB keyboards and mice supported
- On screen display has comprehensive channel selection and security features
- Choose PS/2, USB, or Sun (8-pin) style computers cables
- Rack mountable in a standard 19 inch rack
- Flash upgradeability ensures support for future devices
- Units may be synchronised to enable simultaneous switching of multiple video heads

#### **SPECIFICATION:**

AVM108MP: 1 x USB keyboard, mouse and monitor ports to 8 CPUs.

#### **CPU Connectors**

AVM108MP Model: 8 x 15 way HD D Female for CPU video. 8 x 6 way mini DIN Female for CPU keyboard. 8 x 6 way mini DIN Female for CPU mouse

#### **Console Connectors**

1 x USB type A connector for controlling keyboards. 1 x USB type A connector for controlling mice. 1 x 15 way HD D Female for controlling monitors. 1 x 5V DC 2A power inlets for external PSU. 1 x D9 way Female for Flash upgrade, RS232 control, expansion and remote connectivity accessories.

#### **Features**

- · Advanced On Screen Display up to 16 different passwords and user profiles can be stored on the Matrix
- Flash upgradeable firmware as new drivers are released, free upgrades can be downloaded from the Adder website.
- Front panel keys used for selecting users and channels manually. Also used for selecting auto-scan.
- Front panel display 7 Segment display (red) shows the currently selected CPU. 7 Segment display (green) shows the currently selected user
- Indicators show keyboard and mouse activity.
- Selection methods convenient switching using On Screen Display menu, selectable keyboard hot-key, 3 button mouse, front panel key or RS232 serial control.
- Hot connection of devices can be connected to many running PCs without reboot by using the keyboard and mouse reset feature.
- On the fly configuration the Matrix 108 MP can be configured using the OSD menu.
- User definable hot-key commands can be used for quick channel selection.
- Expandable where the size of your installation is beyond the scope of a single Matrix 108 MP, additional units can be cascaded. This will allow you to use multiple units to provide a video-switching network.
- Auto-scan the Matrix 108 MP can be set to automatically scan all ports or all active ports at a user definable rate.
- Automatic mouse conversion PS/2, IntelliMouse and RS232 type mice are all supported between switch and CPUs. Controlling mouse/trackball is PS/2 type.
- Mouse control of OSD menu.
- Name search facility in OSD menu.
- User may select exclusive or shared computer access.
- Keyboard and mouse reset features for each user port.
- Optional CPU reminder banner may be transparent and moved around the screen.
- Upload and download of OSD configurations to a PC file or Excel spreadsheet.
- Cascaded units do not need to be configured.

### **Physical**

AV108MP - All metal case (WxDxH) 482x205x45 mm

Power - 5V DC, 2A.

EMC - 89/336/EEC CE marked.

LVD - 73/23/EEC.

### Accessories

# **Rack options**

RMK1 19" 1U rack mount kit for AdderView Matrix AV108MP

# **Upgrade cable**

CAB-9M/9F-2M PC to AdderView Matrix MP upgrade cable

### **CPU to AdderView Matrix MP cables**

VKKVM-0.5M 0.5m "3-in-1" cable for PS/2

VKVM-1M 1m "3-in-1" cable for PS/2

VKVM-2M 2m "3-in-1" cable for PS/2

VKVM-5M 5m "3-in-1" cable for PS/2

VKVM-10M 10m "3-in-1" cable for PS/2

CCUSB 2m "3-in-1" cable for USB

CCUSB-5M 5m "3-in-1" cable for USB

CCUSB-10M 10m "3-in-1" cable for USB

CCSUN 2m "3-in-1" cable for SUN

CCSUN-5M 5m "3-in-1" cable for SUN

CCSUN-10M 10m "3-in-1" cable for USB