

Shinybow SB-3776 1:2 SHINYBOW COMPONENT VIDEO DISTRIBUTION AMPLIFIER SPLITTER

1x2 Component Video Distribution Amplifier. Model SB-3776

The 1x2 Component Video Distribution Amplifier is designed to work as a splitter for component video applications. Primarily made to split a Component Video signal from one source to two devices with compatible inputs. A built in amplifier will boost the signal to the needed level, to prevent signal loss and picture degradation. A maximum bandwidth of 300MHz will support a sharp and highly defined video in multiple resolutions of up to 1080p. The 1x2 Distribution Amplifier works with satellite and cable set-top boxes, DVD players, D-VHS players and all other equipment that is equipped with Component Video Connections.

Features:

- Sends Video to multiple displays at the same time
- Allows connection of 2 video displays
- Supports 480i, 480p, 720p, 1080i and 1080p resolutions
- Installs in seconds

Specifications:

- Video Amplifier Bandwidth: 300MHz
- Resolution: up to 1080p
- Video Input Connectors: 3-RCA 75Ω; (YUV, Y/Pb/Pr, Y/Cb/Cr)
- Video Output Connectors: 2 sets of 3-RCA 75Ω; (YUV, Y/Pb/Pr, Y/Cb/Cr)
- Video Distortion: <1.2db (+/-3db)
- Channel Isolation: >50db
- S/N Ratio: >50db
- Power Consumption: 150mA (max.)
- Power Supply: 12VDC; 300mA

Package Includes:

- 1:2 Distribution Amplifier
- Instruction Manual
- AC/DC Adapter: 12VDC, 300mA

Warranty: 1 year labor/parts manufacturers warranty.