PureLink mx-1800 18x18 Modular Type Digital Matrix Router mx-1800

DESCRIPTION:

The PureLink MX Series was introduced in 2008 as the world's first “modular' cross-platform digital matrix router featuring plug-in boards for HDMI, DVI, and 3G SDI. After two years being deployed around the world in mission critical applications, the MX Series has never had a failure. Thats right, not one breakdown the entire time in its been in service. The MX-1800 provides full matrix switching of up to 18 HDMI, DVI (protected and non-protected), or 3G SDI sources to any or all of 18 outputs, within the same chassis, with a choice of fiber, Cat5, DVI, or HDMI cable extension, depending on the distance and resolution required. Featuring the world's fastest switching response time, legendary reliability and quality, and market-leading experience, PureLink's breakthrough MX Series proves once again, nothing beats a PureLink.

INPUT/OUTPUT BOARDS:

Model	Description	MSRP
MX18RPO	Optional Input Power Board	$999.00
DIS3H	DVI In, 3 ports, HDCP	$1399.00
DOS3H	DVI Out, 3 ports, HDCP	$1399.00
DIS3HA	DVI In, 3 ports, 3.5mm Stereo Audio, HDCP	$1599.00
DOS3HA	DVI Out, 3 ports, 3.5mm Stereo Audio, HDCP	$1599.00
DIS3	DVI In, 3 ports, Digital Audio, Non- HDCP	$799.00
DOS3	DVI Out, 3 ports, Digital Audio, Non-HDCP	$799.00
HIS3	HDMI In, 3 ports, HDCP	$1499.00
HOS3	HDMI Out, 3 ports, HDCP	$1499.00
SIS3	HD-SDI In, 3 ports	$1199.00
SOS3	HD-SDI Out, 3 ports	$1399.00
CIS3	CAT5 In, 3 ports	$1299.00
COS3	CAT5 Out, 3 ports	$1299.00
FIS3	Fiber In, 3 ports	$1499.00
COS3	Fiber Out, 3 ports	$1499.00

SPECIFICATION:

- Data Rate: 1.65 Gbps(single link DVI) / 2.25 Gbps(single link HDMI™)
- Audio IN/OUT: Digital audio coaxial (DVI board only)
- Power Supply: DC 12V/5A Adapter
- Consumption : 100 Watts/max:120 Watts
- Dimension: 17.2”(W) x 12.4”(D) x 10.25”(H)
- Weight: 17.6 Lbs