

Kramer 101L 1x1 Composite Video Line Amplifier

DESCRIPTION

- The 101L is a high-performance line amplifier for composite video signals. It provides controls to compensate for signal loss inherent in long cable runs.
 - Bandwidth - 500MHz (-3dB).
 - Level (Gain) & EQ (Peaking) Controls - Recessed trimmers to prevent unintentional resetting.
 - Compact MultiTOOLS® - 4 units can be rack mounted side-by-side in a 1U rack space with the optional RK-1 universal rack adapter.
- Rack Adapters: 19" (1U): RK-1

SPECIFICATIONS

INPUT:	1 composite video on a BNC connector, 1Vpp/75ohm.
OUTPUT:	1 composite video on a BNC connector, 1Vpp/75ohm.
MAX. OUTPUT LEVEL:	2.5Vpp.
BANDWIDTH:	500MHz.
DIFF. GAIN:	0.03%.
DIFF. PHASE:	0.03Deg.
S/N RATIO:	75dB.
CONTROLS:	Level: -0.8dB to 6.5dB; EQ.: 0dB to 8dB.
COUPLING:	DC.
POWER SOURCE:	12V DC, 60mA.
	5.32cm x 4.36cm x 7.25cm (2.09" x 1.72" x 2.85") W, D, H.
WEIGHT:	0.15kg (0.33lbs) approx.
ACCESSORIES:	Power supply.
	RK-1 19" rack adapter.